

Energy-Efficient User Association in Cognitive Heterogeneous Networks

Agapi Mesodiakaki, Ferran Adelantado, Luis Alonso, and Christos Verikoukis

ABSTRACT

Due to the ever increasing data traffic demands, which are directly connected to increased energy consumption, it becomes challenging for operators to achieve capacity enhancement while limiting their electric bill. To that end, exploiting the context awareness of future cognitive networks is expected to play a key role. Next generation cellular networks are about to include a plethora of small cells, with users being able to communicate via multiple bands. Given that small cells are expected to be eventually as close as 50 m apart, not all of them will have a direct connection to the core network; thus, multihop communication through neighboring small cells may be required. In such architectures, the user association problem becomes challenging, with backhaul energy consumption being a definitive parameter. Thus, in this article, we study the user association problem in cognitive heterogeneous networks. We evaluate the existing approaches in terms of energy efficiency and show the potential of exploiting the available context-aware information (i.e., users' measurements and requirements, knowledge of the network architecture, and the available spectrum resources of each base station) to associate the users in an energy-efficient way, while maintaining high spectrum efficiency. Our study considers both the access network and backhaul energy consumption, while the performance of the association algorithms is evaluated under two different case study scenarios.

INTRODUCTION

Nowadays, due to the increased need for anywhere anytime connectivity, mobile data traffic demands are growing exponentially. Thus, it becomes urgent for mobile operators to achieve sustainable capacity improvement. In Long Term Evolution (LTE)/LTE-Advanced (LTE-A) networks, the achievable capacity is highly dependent on the channel quality. Due to the use of link adaptation, the modulation and coding scheme (MCS) is adapted to the signal-to-interference-plus-noise ratio (SINR). Therefore, for higher SINR, an MCS of higher order is used, resulting in higher achievable capacity. However, what still remains a challenge is how to guaran-

tee a high SINR. A straightforward solution is to bring the transmitter closer to the receiver, while at the same time mitigating the received interference. Hence, a significant densification of cellular network deployment is expected the forthcoming years.

The benefit of adding more base stations (BSs) is twofold:

- The distance between user equipment stations (UEs) and BSs is reduced; thus, the SINR increases.
- Each UE shares the BS's bandwidth and backhaul (BH) connection with a smaller number of UEs, thus gaining access to a larger portion of resources, which results in extra capacity improvement.

However, adding more macrocell BSs (i.e., eNodeBs, eNBs, in LTE terminology) to the network is not viable in many important markets due to the cost, and the lack of available sites and proper connections among them. Consequently, future cellular networks are expected to be dense deployments of BSs of widely varying transmit powers and coverage areas (i.e., eNBs and/or small cells, SCs), carrier frequencies, BH connection types, and communication protocols. Besides their heterogeneous nature, they will also be characterized by the implementation of cognitive capabilities in some of the involved network entities. In particular, they will be able to i) identify current network conditions (i.e., context awareness); and ii) decide and act according to these conditions, learning from the consequences of their actions, thus forming so-called self-organized networks (SONs). Therefore, in the rest of this article, we refer to these networks as cognitive heterogeneous networks (HetNets).

In next generation cognitive HetNets, UEs will be capable of communicating via multiple bands over various protocols; hence, the user association problem becomes challenging, with future HetNet architecture playing an important role. As SCs are expected to eventually be as close as 50 m apart [1], it is expected that not all of them will have a direct connection to the core network (CN). To that end, LTE-A [2] considers that an SC may be connected to the CN through a gateway, known as the home eNB gateway (HeNB GW). The Next Generation Mobile Network (NGMN) Alliance [3] and Tellabs [4] also consider an optional aggregation gateway to be

Agapi Mesodiakaki and Luis Alonso are with the Technical University of Catalonia.

Ferran Adelantado is with the Open University of Catalonia.

Christos Verikoukis is with the Telecommunications Technological Centre of Catalonia.

introduced for better scalability (e.g., reducing the number of logical S1 interfaces to be supported by the CN). Moreover, assuming that the operator already has a radio access network in place, a straightforward option is to connect the SC directly to the eNB site, especially in cases where there is fiber access available [3, 4]. From the topology perspective, this would look like a traditional hub-and-spoke, with the eNB as the hub and the SCs as spokes, while ring, chain, or mesh topologies can be used between SCs to provide further connectivity, as depicted in Fig. 1 [4].

In such topologies, where one SC backhauls its traffic to the neighboring SC that acts as an aggregation point, the extension and configuration of the BH involves a multidimensional trade-off between the reduction of capital expenditure (CAPEX) and energy consumption, with the consequent reduction of operational expenditure (OPEX) and the maximization of the access network capacity. It is precisely in this context that, for a BH configuration, which is often determined by external constraints, the user association strategy should exploit context-awareness to deal with the aforementioned complexity.

Thus, in this article, we focus on next generation cognitive HetNets and we study the user association problem in scenarios where several SCs backhaul their traffic to the neighboring cells until they reach the CN. We evaluate the performance of the existing user association algorithms and we show the high energy efficiency potential of a cognitive algorithm that exploits the available context-aware information (i.e., UE measurements and requirements, HetNet architecture knowledge, and the available spectrum resources of each BS) to associate the UEs in an energy-efficient way.

The rest of the article is organized as follows. First, the main technical challenges in future cognitive HetNet user association are studied and analyzed. Then the current user association algorithms proposed in the literature along with a new context-aware user association algorithm are discussed. We include the performance comparison of the user association algorithms, where useful insights and conclusions are provided. Finally, we conclude the article.

TECHNICAL CHALLENGES

The main objective of user association in future cognitive HetNets is to achieve network capacity enhancement while satisfying the UE QoS requirements. To that end, three main challenges¹ can be identified: interference management, spectrum efficiency maximization, and energy efficiency maximization.

INTERFERENCE MANAGEMENT

As future HetNets become denser and spectrum resources are limited, high spectrum reuse is necessary to achieve higher spectrum efficiency. Under spectrum reuse, interference management becomes a major concern. User association in future HetNets imposes additional challenges on interference management, since a UE may communicate with a different BS than the one




Figure 1. Future cognitive HetNet topology.

from which it receives the strongest signal. Thus, in this case, the UE experiences strong downlink interference while causing high uplink interference to UEs in its proximity. Furthermore, the complex BH architecture should be taken into account to efficiently avoid/mitigate the generated interference.

Several interference management techniques have been proposed so far. Although fractional frequency reuse is traditionally used, it presents low efficiency, while its complexity increases when applied in dense HetNets consisting of many tiers. Thus, in Releases 8/9 of LTE, intercell interference coordination (ICIC) was introduced, where the intercell interference is controlled by radio resource management (RRM) methods based on cell spectrum usage and traffic load [2]. In enhanced ICIC (eICIC), introduced in Release 10 of LTE-A, the transmissions of multiple cells are coordinated not only in the frequency domain but also in the time domain using power control schemes. Furthermore, aiming to improve interference management, eICIC introduced almost blank subframes (ABSs) during which the eNB remains silent (i.e., only transmitting control information at very low power), thus enabling the UE communication with their associated SCs without interference caused by the eNB [2].

In general, in future cognitive HetNets, user association and interference management constitute two interdependent problems, and therefore should be jointly studied and designed.

SPECTRUM EFFICIENCY MAXIMIZATION

Due to the previously explained spectrum scarcity problem, spectrum efficiency maximization (i.e., maximization of the achievable data for a given spectrum band) is another challenge mobile operators have to meet. This metric is directly connected to the achieved SINR. Specifically in LTE-A networks, the spectrum efficiency of a UE is a scalar step function of its SINR, with each step corresponding to the use of a specific MCS and thus to a specific achievable rate [5].

¹ Resource allocation fairness is another main HetNet challenge, but it has not been included since it is a cross-cutting objective that encompasses the three main challenges discussed in this article and all the radio resource management functions, particularly scheduling.

Maximizing network energy efficiency may be defined as maximizing the successfully sent data while minimizing the total energy consumption. In the case of specific UE requirements, this can be expressed as satisfying the UE traffic demands while minimizing the total energy consumption.

Network densification is expected to improve the overall spectrum efficiency, since the distance between UEs and BSs decreases, and thus higher SINR is achieved. In LTE, further spectrum efficiency enhancement is provided by multiple-input multiple-output (MIMO) technology and carrier aggregation. MIMO, which uses multiple antennas at both the transmitter and receiver, offers significant increases in data throughput and link range without additional bandwidth or increased transmit power. On the other hand, through carrier aggregation higher data rates are achieved, since the overall used bandwidth increases.

In future cognitive HetNets, a UE may not always be connected to the BS from which it receives the highest SINR. Hence, spectrum efficiency becomes even more challenging, stressing the need for spectrum-aware user association strategies.

ENERGY EFFICIENCY MAXIMIZATION

Maximizing network energy efficiency may be defined as maximizing the successfully sent data while minimizing the total energy consumption. In case of specific UE requirements, this can be expressed as satisfying the UE traffic demands, while minimizing the total energy consumption.

The total energy consumption is the sum of the energy consumed in the access network, that is, between the UE and the BS (Uu interface) and in the BH links (i.e., between BSs and/or the CN). The BH energy consumption definitely impacts the overall energy efficiency, especially when considering scenarios as the ones previously described with BH links, and thus cannot be neglected.

Given the common assumption that the total transmit power of a BS is equally distributed among its subcarriers [6], the energy consumed in the access network is a function of the number of resource block pairs (RBPs) needed to serve the UE traffic. The more RBPs allocated to the UE, the higher the access network energy consumption to serve the UE traffic. Also note that as eNBs have a much higher total transmit power than SCs, the power allocated to an RBP, and thus the access network energy consumption is higher when a UE is associated with an eNB than with a SC.

Then the BH link energy consumption is a scalar function of the aggregated throughput that passes through the link (i.e., the sum of the total throughput of all UEs associated with the SCs that backhaul their traffic through this link). Specifically, given that adaptive MCS is used, the energy consumption in a BH link can be expressed as a function of the aggregated throughput and thus of the required SINR to achieve this throughput. This function depends on the employed BH technology and the distance between the transmitter and the receiver of the BH link. Depending on the UE association, the BH energy consumption may vary significantly. The closer the serving BS to the CN (i.e., the fewer hops until the data packets reach the CN), the less the BH energy consumption. In addition, further energy efficiency gains can be achieved when BH load balancing is per-

formed, since the energy consumption of a BH link does not increase linearly with its traffic load [5].

Overall, the network energy efficiency is highly dependent on the UE association decision, with BH energy consumption having a significant impact. As a result, user association algorithms taking into account both the access network and BH energy consumption should be designed.

USER ASSOCIATION ALGORITHMS

During the last few years, the UE association problem has received a lot of research attention. To that end, the most important user association algorithms may be summarized in the following.

REFERENCE SIGNAL RECEIVED POWER

In LTE-A, the user association is based on the reference signal received power (RSRP) and/or reference signal received quality (RSRQ). The first measures the average received power over the resource elements that carry cell-specific reference signals within certain frequency bandwidth, while the latter measures the portion of pure reference signal power over the total power received by the UE. Although these criteria maximize the SINR of UEs [7], simulations and field trials have shown that they do not increase the overall throughput as much as hoped, because many SCs typically have few active UEs. This stems from the fact that the transmit power of an SC is much lower with respect to the eNB, resulting to a smaller downlink SC coverage. However, this is not the case for the uplink, where the UE transmission range is the same for all UEs. The algorithm presents high spectrum efficiency, as the UE gets associated with the BS from which it receives the strongest signal. However, its energy efficiency cannot be guaranteed, since it only considers the radio access network.

RANGE EXPANSION

Reference signal received power presents relatively poor overall throughput performance since most UEs get connected to the eNB, whereas many SCs have few active UEs. To that end, range expansion (RE) was proposed, which adds a *bias* (in dB) to the RSRP in the case in which the signal is transmitted from an SC, thus actively pushing UEs onto SCs [8, 9]. Despite a potentially significant SINR hit for that UE, this has the potential for a win-win situation, because the UE gains access to a much larger portion of resources, while the eNB reclaims the ones that would have been allocated to it. Range expansion presents lower spectrum efficiency than RSRP, especially in cases when an aggressive bias is used, as a UE is connected to a BS that does not provide the highest SINR. Finally, equivalent to RSRP, its energy efficiency cannot be guaranteed.

MINIMUM PATH LOSS

A UE is connected to the BS from which it has minimum path loss (MPL), regardless of its received power [6]. In ideal environments with no fading, the algorithm would connect the UE to its closest BS. In hotspot traffic distribution scenarios, MPL achieves maximum traffic

offloading to SCs, since most UEs will be associated with SCs in their proximity. Moreover, it achieves much lower spectrum efficiency than the maximum as SINR is not taken into account in the user association decision. Although MPL minimizes the UE power consumption in the uplink, it fails to guarantee high network energy efficiency due to high BH energy consumption.

CONTEXT-AWARE ALGORITHM

All the aforementioned approaches consider only the access network, thus totally overlooking any BH issues. Still, the BH is forecast to become the most challenging part for future SCs, especially when considering scenarios as those previously described with wireless BH links. In such scenarios, the BH energy consumption can be responsible for a high percentage of the total energy consumption and consequently cannot be ignored.

Thus, we propose a context-aware algorithm (CA), summarized in Fig. 2, that takes as input the available context-aware information (i.e., the UEs' measurements and requirements, the Het-Net architecture knowledge, and the available spectrum resources of each BS) to associate the UEs aiming to maximize the network energy efficiency. Note that this context-aware information can be readily available to all nodes in an LTE-A network, while introducing low overhead (e.g., by transmitting it during the ABSs or through the X2 interface between BSs [eNBs and/or SCs]) [2].

At the same time, CA achieves high spectrum efficiency, since only the BSs that require the minimum number of RBPs to satisfy the UE requirements (i.e., the BSs with the best received SINR) are included in the UE candidate cell set. To ensure that all the UEs will be associated, CA sorts the UEs by number of candidates and starts with the ones with the fewest candidates.

Then, to maximize the network energy efficiency, CA sorts the candidate cells by the number of hops until their traffic reaches the CN, and it associates the UE to the candidate with the fewest hops as long as it has sufficient RBPs to serve it. Otherwise, it moves to the next candidate. Every time a UE is associated with a BS, the algorithm updates the remaining RBPs of the BS, its cell throughput, and the throughput that passes through the BH links that are used until its traffic reaches the CN. In case there are more candidates with the same number of hops, CA associates the UE to the one with the least loaded BH route, as long as it has sufficient RBPs to achieve load balancing at the BH links.

In terms of scalability, CA may be executed in each eNB sector at a specific time interval based on the dynamics of the UE traffic distribution so that the system performance is optimized. For the new UEs that appear in the meantime, CA is executed as before given the associations of the rest of the UEs. However, in that case, the context-aware information includes the remaining RBPs and the throughput of each BS/cell, and the throughput that passes through each BH link given the traffic of the already associated UEs.




Figure 2. Context-aware algorithm flowchart.

PERFORMANCE EVALUATION

In this section, we evaluate the performance of the previously discussed user association algorithms in terms of spectrum efficiency and energy efficiency, aiming to gain useful insights on their ability to meet future cognitive HetNet challenges.

SCENARIOS

In our experiments, we consider a sector area of an eNB, which overlaps five outdoor SCs. In order to study the impact of the BH architecture on the algorithm performance, two different BH architecture scenarios are employed, as depicted in Figs. 3a and 3b. Notice that although the same BS deployment is considered in both scenarios, the BH architecture varies significantly (i.e., SCs 3 and 5 are connected through SC 4 in the second scenario). In general, this may happen due to deployment impairments (e.g., buildings) that impose restrictions on the actual BH link configurations.

The BH network consists of line-of-sight (LOS) millimeter-wave (mmW) links (60 GHz band) with 50 MHz channel bandwidth [10], whereas the access network operates at 2.0 GHz with 10 MHz bandwidth available to the eNB and to each SC. The association of the received SINR to the achievable spectral efficiency in bits per second per Hertz can be found in [5, Table A.2], while the mmW link budget equation is given by [10, eq. 1.4]. In each simulation realiza-




Figure 3. Simulation topology scenarios considering different BH architectures: a) BH architecture 1; b) BH architecture 2.

tion we considered N fixed outdoor UEs of different throughput requirements. Specifically, 80 percent of UEs demand 500 kb/s, 10 percent 700 kb/s, and 10 percent 1 Mb/s. The maximum transmit power was equal to 46 dBm for the eNB and 30 dBm for a SC, while path loss models and other setup parameters were selected according to 3GPP recommendations [11].

We further considered two user distribution scenarios. In the first (scenario 1), the UEs are uniformly distributed in the sector area of radius $R = 450$ m, while in the second (scenario 2), they form hotspots. In particular, in scenario 2, we consider that 40 percent of the UEs are uniformly distributed in a radius $r = 60$ m from SC 3, another 40 percent in a radius $r = 60$ m from SC 4, and the rest uniformly distributed in the whole sector area. Note that this scenario constitutes a more realistic scenario, as in future Het-Nets the UEs are expected to be very close to SCs and to generate hotspot traffic highly bursty in nature [1]. The four user association algorithms described earlier have been simulated in both scenarios.

RESULTS

Maximizing network energy efficiency becomes more challenging as the number of UEs increases. Therefore, in our experiments, we consider highly loaded scenarios consisting of more than 60 UEs.

In terms of throughput, all algorithms achieve the same performance in both scenarios (e.g., for $N = 100$ UEs, the total network throughput is 57 Mb/s), as all algorithms ensure that UEs' demands are satisfied.

As far as the network energy efficiency of scenario 1 is concerned, CA achieves slightly better performance than RSRP for values higher than $N = 70$ UEs, as depicted in Fig. 4a. This is due to the fact that CA gives priority to the candidate cell with the fewest hops, so most UEs get connected to the eNB. In this case, the

additional energy consumption experienced by CA in the Uu interface with respect to RSRP is not compensated for by the reduction of the BH energy consumption. However, for higher values, there are no available RBPs in the eNB at some point; thus, UEs are associated with the candidate SC with the fewest hops, which results in lower BH energy consumption compared to RSRP. This can also be noticed in Fig. 4b, where the average traffic of each BH link of Fig. 3a is depicted for $N = 100$ UEs. According to this, CA achieves better load balancing among the BH links that are the same number of hops away from the CN (e.g., among BH links 4 and 5) than the other algorithms. As far as RE is concerned, it achieves lower energy efficiency, since there are more UEs associated with SCs, resulting in higher BH energy consumption. Finally, MPL can be considered as an aggressive RE algorithm, where it is likely for the UEs to be closer to an SC and thus associated with it. Although MPL achieves maximum traffic offloading to SCs, it has very poor energy efficiency performance, as the BH traffic (Fig. 4b) and thus the BH energy consumption are much higher than those of the other approaches.

In Fig. 4c, the average network energy efficiency of all algorithms is depicted when scenario 2 is applied. In this case, CA achieves gains up to 100 percent, since it manages the BH traffic so that lower energy consumption is generated. Specifically, in comparison to RSRP, CA achieves up to 40 percent energy efficiency gain. This stems from the fact that the UEs located around SC 3 or 4, which have as candidate cells SC 1 or 2, will be associated with SC 3 or 4 when RSRP is applied, given that they receive higher SINR, whereas to SC 1 or 2 with CA, given that fewer hops are required to reach the CN. As a result, CA generates globally less traffic for the BH links, and thus the BH energy consumption becomes




Figure 4. Performance evaluation results for the simulation scenario with BH architecture 1, depicted in Fig. 3a: a) average network energy efficiency for different number of users (N), when the UEs are uniformly distributed in the sector area (scenario 1); b) average traffic of each backhaul link for scenario 1 for $N = 100$ UEs; c) average network energy efficiency for different number of users (N) for hotspot traffic (scenario 2); d) average traffic of each backhaul link for scenario 2 when $N = 100$ UEs.

much lower. This is better explained in Fig. 4d, where the average traffic of each BH link is depicted for scenario 2, when $N = 100$ UEs. As shown, CA again achieves much better BH load balancing (e.g., the UEs around SC 4 that have as a candidate cell, SC 5, will be connected to the SC that has the least loaded BH route). Then, as far as RE is concerned, it has poor energy efficiency performance, since there are more UEs associated to SCs than in RSRP; hence, it presents higher BH energy consumption. Finally, MPL presents the lowest energy efficiency, since most UEs are associated with the closest SCs, resulting in the most highly loaded BH links (Fig. 4d) and consequently the highest BH energy consumption.

When the BH architecture scenario of Fig. 3b is applied, the total network energy efficiency, under the same user distribution scenarios (Figs. 5a and 5c), is lower than in the previous BH architecture scenario. This is due to the fact that the number of hops has a strong impact on BH energy consumption (SCs 3 and 5 are now three hops away from the CN). Thus, apart from the need for careful design of the BH architecture,

backhaul-aware user association strategies should be developed with the aim of achieving high network energy efficiency.

In Figs. 5b and 5d, the average traffic of each BH link for $N = 100$ UEs for the BH architecture of Fig. 3b is depicted, when scenarios 1 and 2 are applied, respectively. In comparison to Figs. 4b and 4d, it can be observed that the BH traffic distribution may differ significantly when the BH architecture changes. This fact justifies the need for backhaul-aware user association strategies, especially in dense deployment scenarios. To that end, unlike the rest of the algorithms, CA takes into account both the access network and BH information in a dynamic way to achieve energy efficiency gains. For instance, notice that in the previous BH architecture, load balancing was applied between BH links 1, 2, and 3, and in this architecture between BH links 1 and 2, since they are the same number of hops away from the CN. It is also worth noting that due to its backhaul awareness, CA could also deal with BH link failures.

In Fig. 6, the average network spectrum efficiency is depicted for all algorithms. This metric

was shown to be independent of the applied BH architecture scenario. However, it highly depends on UEs' SINR and consequently on UEs' distribution. As shown in Fig. 6, CA achieves equally high spectrum efficiency as RSRP and RE for both user distribution scenarios, since it achieves the same throughput with the same amount of total RBPs used. In particular, the high spectrum efficiency of CA stems from basing the user association not only on the BH configuration, but also on the link quality (i.e., CA considers as candidate cells for a UE only the cells with the highest SINR that satisfy the UE requirements). MPL, unlike the rest of the algorithms, presents much lower spectrum efficiency, as it associates the UEs regardless of their SINR. Thus, a UE may be associated with an SC having the minimum path loss, although its received SINR is lower, and therefore more RBPs will be needed to achieve the same throughput. Moreover, notice that MPL achieves higher spectrum efficiency in scenario 2 than in scenario 1. This is due to the fact that UEs which form a hotspot around an SC will have both low path loss and high SINR received from it, and thus will need a

lower number of RBPs to satisfy their requirements.

CONCLUSION

In this article, we study the user association problem in future cognitive HetNets, where several SCs forward their traffic through the BH to neighboring SCs until it reaches the CN. Interference management, spectrum efficiency maximization, and energy efficiency maximization are identified as the main technical challenges in this field that future user association solutions should meet. The performance of the existing user association algorithms is evaluated in terms of energy efficiency and spectrum efficiency under two different user distribution scenarios. The BH energy consumption is shown to play a key role in the overall network energy efficiency, thus predicating the development of energy-efficient backhaul-aware user association strategies. To that end, we propose a context-aware algorithm that takes into account both the access network and BH conditions to associate the UEs in an energy-efficient way, while achieving up to two




Figure 5. Performance evaluation results for the simulation scenario with BH architecture 2, depicted in Fig. 3b: a) average network energy efficiency for different number of users (N) when the UEs are uniformly distributed in the sector area (scenario 1); b) average traffic of each backhaul link for scenario 1 for $N = 100$ UEs; c) average network energy efficiency for different numbers of users (N) for hotspot traffic (scenario 2); d) average traffic of each backhaul link for scenario 2 when $N = 100$ UEs.

and a half times more total energy efficiency than the reference algorithms.

ACKNOWLEDGMENT

This work has been funded by the Research Projects GREENET (PITN-GA-2010-264759), GREEN-T (CP8-006), GEOCOM (TEC2011-27723-C02-01), COST-TERRA (IC0905), and CROSSFIRE (MITN-317126).

REFERENCES

- [1] Small Cell Forum, "Backhaul Technologies for Small Cells: Use Cases, Requirements and Solutions".
- [2] 3GPP TS 36.300, "E-UTRA & E-UTRAN Overall Description," v. 11.5.0, Rel. 11.
- [3] NGMN Alliance, "Small Cell Backhaul Requirements," v. 1.0, June 2012.
- [4] Tellabs, "Small Cells Address the Growing Demand for Data," 2012.
- [5] 3GPP TS 36.942, "Radio Frequency (RF) System Scenarios," v. 11.0.0, Rel. 11.
- [6] D. Fooladivanda and C. Rosenberg, "Joint Resource Allocation and User Association for Heterogeneous Wireless Cellular Networks," *IEEE Trans. Wireless Commun.*, vol. 12, no. 1, Oct. 2012, pp. 248–57.
- [7] H. S. Dhillon et al., "Modeling and Analysis of K-Tier Downlink Heterogeneous Cellular Networks," *IEEE JSAC*, vol. 30, no. 3, Apr. 2012, pp. 550–60.
- [8] NTT DOCOMO, "Performance of eCIC with Control Channel Coverage Limitation," R1-103264, 3GPP Std., May 2010.
- [9] A. Damjanovic et al., "A Survey on 3GPP Heterogeneous Networks," *IEEE Wireless Commun.*, vol. 18, no. 3, June 2011, pp. 10–21.
- [10] K.-C. Huang and Z. Wang, *Millimeter Wave Communication Systems*, Wiley, 2011.
- [11] 3GPP TS 36.814, "Further Advancements for E-UTRA Physical Layer Aspects," v. 9.0.0, Mar. 2010.

BIOGRAPHIES

AGAPI MESODIAKAKI (agapi.mesodiakaki@tsc.upc.edu) obtained her five-year diploma (M.Sc.) in electrical and computer engineering from the National Technical University of Athens (NTUA) in February 2011. During her studies, she accomplished a couple of internships at the Hellenic Telecommunications Organization (OTE S.A) of Greece and TU Darmstadt, Germany. Currently, she is a Marie Curie early stage researcher, pursuing a Ph.D. degree at the Signal Theory and Communications Department (TSC) of the Universitat Politècnica de Catalunya (UPC), Barcelona.

FERRAN ADELANTADO (ferranadelantado@uoc.edu) received his degree in telecommunications engineering from UPC in December 2001. In June 2002 he joined the Radio Communications Research Group at UPC, where he completed his Ph.D. in May 2007. Since December 2007 he has been working as an associate professor at Universitat Oberta de Catalunya (UOC). Also from UOC, he received his B.S. in business sciences in July 2012. He has participated in several funded European and National projects, such as SOFIA, COSMOS, EVEREST, CAUTION, AlgorithmsForRealRouting, and CROSSFIRE.




Figure 6. Average network spectrum efficiency for both UE traffic distribution scenarios.

LUIS ALONSO (luisg@tsc.upc.edu) obtained his Ph.D. from UPC in 2001 and got a permanent tenured position at the same university, becoming an associate professor in 2006. He was co-founder of the Wireless Communications and Technologies Research Group (WiComTec), to which currently belongs. He is an author of 40 research papers in international journals and magazines, one book, 12 chapters of books, and more than 100 papers presented at international congresses and symposia. He has received several best paper awards.

CHRISTOS VERIKOUKIS (cveri@cttc.es) got his Ph.D. from UPC in 2000. He is currently a senior researcher and head of the SMARTTECH Department at CTTC and an adjunct professor at the University of Barcelona. He has published 60 journal papers and over 130 conference papers. He is also a co-author of two books, 14 book chapters, and two patents. He has supervised 15 Ph.D. students and 5 post-doctoral researchers since 2004. He participated in more than 30 competitive projects while he served as Principal Investigator in national projects in Greece and Spain as well as Technical Manager in Marie Curie and Celtic projects. He has been appointed to serve as a reviewer of FP7 projects funded by the European Commission and as an EU-independent expert acting evaluator of different FP7 funding mechanisms. He was General Chair of the 17th and 18th IEEE Workshops on Computer-Aided Modeling, Analysis and Design of Communication Links and Networks (CAMAD) and TPC Co-Chair of the 15th IEEE International Conference on E-health Networking, Application & Services (Healthcom). He is currently an officer (Secretary) of the IEEE ComSoc Technical Committee on Communication Systems Integration and Modeling (CSIM). He received the best paper award of the Communication QoS, Reliability & Modeling Symposium at IEEE ICC '11 and the EURASIP 2013 Best Paper Award for the *Journal on Advances in Signal Processing*.